

Broadband Manpack Antenna



The SINGGAR tactical blade antenna is designed to be used in military manpack applications where reliability is needed most. This antenna works with all SINGGAR radios.

The traditional connector provided with the antenna is a modified BNC connector with a 1/2-28 UNEF thread.

The radiator is constructed of layered stainless steel leaf springs and is protected by a tough outer neoprene sheath. The radiator and base are connected by a gooseneck for various angle possibilities.

All exposed metallic surfaces are protected with Prolane-T black 2 part polyurethane paint.



Broadband Manpack Antenna

Specifications

ELECTRICAL:

| | |
|---------------------------|---------------------------------|
| Frequency Range: | 30-90 MHz |
| Input Impedance: | 50 Ω Nominal |
| Power: | 35 Watts |
| Polarization: | Vertical |
| Radiation Pattern: | Azimuth: 360° Elevation: 90° |
| Input Connector: | BNC |

MECHANICAL:

| | |
|------------------------|----------------------|
| Overall Height: | 51 in. (1.30 m) |
| Net Weight: | 1 lb. (0.45 kg) |
| Color: | Black/Green/Tan/Grey |
| Mounting: | BNC |

****All information on this product and the product itself is the property of and is proprietary to Hascall-Denke.**

****Specifications are subject to change without prior notice.**



Made in the USA
ISO 9001:2015 Certified
(1Y07900)

P.O. Box 909, Palmetto, Florida 34220-0909
Tel: 941-723-2833 • Fax: 941-723-1628
www.hascall-denke.com