



MPMP136-174/380-520

136-174 & 380-520 MHz

Dual Band VHF/UHF Radio Antenna

The MPMP136-174/380-520 is designed to provide maximum performance and superior reliability for the Kenwood NX-210 radios. This dual band VHF/UHF antenna can achieve 7-10 dB increase in gain in the VHF band and 3-7 dB increase in the UHF band over the stock antenna.

**Extend Antenna for
Maximum Performance
in VHF band**

**Fold Antenna to Blue Line
for Maximum Performance
in UHF Band**



Features

- 3-10 dB increase in gain over stock antenna
- Foldable Radiator
- Operates in folded position
- Extends range
- Robust construction

Electrical Specifications

Frequency	136-174 & 380-520 MHz
Polarization	Vertical
Impedance	50 Ω Nominal
VSWR	< 2:1
Gain	3-10 dBi improvement over stock
Radiation Pattern	Azimuth 360°
Power	10 Watts
Connector	SMA Male

Mechanical Specifications

Design	Monopole
Weight	3.1 oz (88 grams)
Height	20.5 in. (0.53 m)
Radio	Kenwood NX-210
Color	Black

**All information on this product and the product itself is the property of and is proprietary to Hascall-Denke.

**Specifications are subject to change without prior notice.

Made in the USA

www.hascall-denke.com


1Y53900

**ISO 9001 Certified
Form F042, Rev: A**

**12285 U.S. Highway 41 N., Palmetto, FL 34221
1-800-473-2139**



Signal Strength Comparison



VSWR

